



by Honeywell

Velociti® Series ASD-PL2F, ASD-PTL2F and ASD-PL2FR

Description

The Gamewell-FCI Velociti® Series, analog addressable plug-in smoke sensors with integral communication provide features that surpass conventional sensors. Sensitivity can be programmed in the control panel software, and is continuously monitored and reported to the panel. Point ID capability allows each sensor's address to be set, providing exact locations for selective maintenance when the chamber contamination reaches an unacceptable level. The ASD-PL2F photoelectric sensor's unique optical sensing chamber is engineered to sense smoke produced by a wide range of combustion sources. Dual electronic thermistors add 135°F (57°C) fixed-temperature thermal sensing on the ASD-PTL2F model.

The Velociti® Series use a communication protocol that substantially increases the speed of communication between the sensors and certain Gamewell-FCI analog addressable fire alarm controls. These devices operate in a grouped fashion. If one of the devices in the group has a status change, the panel's microprocessor stops the group poll and concentrates on the single device. The net effect is a response speed up to five times greater than earlier designs.

Ordering Information

Model	Description
ASD-PL2F	Analog, addressable photoelectric smoke sensor
ASD-PTL2F	Analog, addressable photoelectric smoke sensor with thermal sensing
ASD-PL2FR	Analog, addressable photoelectric smoke sensor used with the DNR duct base when the remote test is required.

Velociti® is a registered trademark of Honeywell International Inc.
UL® is a registered trademark of Underwriters Laboratories Inc.

Analog, Addressable Photoelectronic Smoke Sensor



ASD-PL2F/ASD-PTL2F



ASD-PL2FR

Features

- Sleek, low-profile design
- Visual rotary, decimal switch addressing (01-159)
- Built-in functional test switch activated by an external magnet
- Bicolor LEDs flash green whenever the sensor is addressed, and light steady red on alarm*
- Optional relay, isolator, or sounder bases
- Low standby current
- Analog addressable communication
- Stable communication technique with noise immunity
- Optional remote, single-gang LED Indicator (RA400Z)
- Compatible with Gamewell-FCI analog addressable panels

Note: *Only the red LED is operative in panels that do not operate in Velociti® mode.

An ISO 9000-2000 Company

SIGNALING



MEA Approved



219-02-E Vol.VI 7272-1703:121

GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1653 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

©2010 by Honeywell International Inc. All rights reserved.

www.gamewell-fci.com

9020-0617 Rev. G page 1 of 2

Installation

ASD-PL2F plug-in sensors use a separate base to simplify installation, service, and maintenance. A special tool allows maintenance personnel to plug-in and remove sensors without using a ladder.

Mount the base on a box which is at least 1.5" (3.8 cm) deep. Suitable mounting base boxes include:

- 4.0" (10.2 cm) square box
- 3.5" (8.9 cm) or 4.0" (10.2 cm) octagonal box
- Single-gang box (except relay or isolator bases)
- With B200SR base, mounted on a 4.0" (10.2 cm) square box
- With B224RB or B224BI base, mounted on a 3.5" (8.9 cm) octagonal box, or a 4.0" (10.2 cm) octagonal or square box

NOTE: Because of the inherent supervision provided by the SLC, end-of-line resistors are not required. Wiring "T-taps" or branches are permitted for Style 4 (Class "B") wiring.

Sensor Spacing

Gamewell-FCI recommends spacing sensors in compliance with NFPA 72. In low airflow applications with smooth ceilings, space sensors 30 feet (9.1 m). For specific information regarding sensor spacing, placement and special applications, refer to NFPA 72.

Specifications

Size: 2.1" (5.1 cm) high x 4.1" (10.4 cm) diameter installed in the B501 base, 6.1" (15.5 cm) diameter installed in the ADB-FL base.

Shipping Weight: 5.2 oz. (147 g)

Operating

Temperature: ASD-PL2F:
32° F to 120° F (0° C to 49° C)
ASD-PTL2F:
32° F to 100° F (0° C to 38° C)

UL®-Listed

Velocity Range: 0-4000 ft./min. (1,219.2 m/min.), suitable for installation in ducts.

Relative

Humidity: 10-93% (non-condensing)

Thermal Ratings: Fixed-temperature setpoint
135° F (57° C)

Electrical Specifications

Voltage Range: 15 – 32 volts DC peak

Standby Current: (max. avg.): .0003 A @ 24 VDC
(one communication every 5 seconds with LED enabled)

Maximum Alarm

Current: .0065 A @ 24 VDC (LED) lit).

Bases and Options

ADB-FL 6.1" (15.5 cm) diameter
B200SR 6.875" (17.46 cm) Base Diameter
2.0" (5.08 cm) Base Height

B224RB

Relay Base

Screw terminals:
Up to 14 AWG (2.0 mm²)
Relay type: Form-C
Rating:
2.0A @ 30 VDC resistive;
0.3 A @ 110 VDC inductive;
1.0 A @ 30 VDC inductive.

Dimensions:
6.2" x 1.2" (15.7 x 3.0 cm)

Maximum: 25 devices between isolator bases.

RA400Z

Remote alarm indicator, LED.

BCK-200

Black detector covers (box of 10)

DNR

Duct smoke housing

GAMEWELL-FCI