

by Honeywell

## Description

The LCD-E3 provides the main panel display of the E3 Series® Expandable Emergency Evacuation System with indicating LEDs and operating switches. Up to six (6), LCD-E3 displays may be locally or remotely located from the panel via a local RS-485 bus of the ILI-MB-E3/ILI95-MB-E3 sub-assembly.

The LCD-E3 includes an LCD display for the system status and the following switches and LED indicators:

### Switches

- Alarm acknowledge
- Trouble acknowledge
- Signal silence
- System reset/lamp test
- Function buttons:
  - menu/back
  - back space/edit
  - OK
- 12 button keypad

### LED Indicators

- AC Power On (green)
- Alarm (red)
- Supervisory (yellow)
- System Trouble (yellow)
- Power Fault (yellow)
- Ground Fault (yellow)
- System Silenced (yellow)

## Installation

The LCD-E3 is adaptable for installation in any of the following E3 Series® System cabinets:

- "A" size cabinet, inner door (E3ID2-A)
- "A2" size cabinet, inner door (E3ID-A2)
- "B" size cabinet, inner door (E3ID2-B)
- "C" size cabinet, inner door (E3ID2-C)
- "D" size cabinet, inner door (E3ID2-D)

## Specifications

- Operating Voltage:** 24 VDC FWR  
(from PM-9 power supply)
- Operating Current:** 0.024 amp
- Alarm Current:** 0.028 amp
- Operating Temperature:** 32° to 120° F (0° to 49° C)
- Relative Humidity:** 0 to 93%, non-condensing at 90° F (32° C)

E3 Series® and NetSOLO® are registered trademarks of Honeywell International Inc.

## LCD Keypad Display



LCD-E3

## Features

- Listed under UL Standard 864, 9th Edition
- Provides an 80-character display of system events together with indicating LEDs and control switches
- The ILI-MB-E3/ILI95-MB-E3 can support up to six (6), LCD-E3 displays, any or all of which may be remotely located via the RS-485 serial interface
- Easy to read backlit LED display, low power consumption

## Ordering Information

Model	Description
LCD-E3	LCD keypad display

### An ISO 9001-2000 Company



### GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

©2011 by Honeywell International Inc. All rights reserved.

[www.gamewell-fci.com](http://www.gamewell-fci.com)

9020-0606 Rev. H page 1 of 1